

GDS-1000B Series

100MHz/70MHz/50MHz Digital Storage Oscilloscope

FEATURES

- **100/70/50MHz Bandwidth Selections, 2ch or 4ch Input**
- **1GSa/s Maximum Sampling Rate**
- **10M Maximum Memory Depth For Each Channel**
- **3" 800 x 480 WVGA LCD Display**
- **256 Color Gradient Display Function to Strengthen Waveform Performance**
- **14bits FFT Frequency Domain Signal Display**
- **Zero Key Function For Horizontal Time, Vertical Voltage and Triggering**
- **Compact and Innovative Exterior Design**

Realizing Professional Functionalities with an Entry-Level Pricing

The GDS-1000B Series features three bandwidth selections - 100 MHz, 70 MHz, 50 MHz, and equips with analog input terminals by four or two channels(50MHz, 4 channels input), The maximum sampling rate for each single channel is 1GSa/s, and the memory depth is 10Mpts per channel independently. The GDS-1000B Series has a waveform update rate of 50,000wfms/s, which helps users to precisely observe the waveform variation. Additionally, 7" WVGA color LCD display and the 256 color gradient display function together allow waveforms to be observed with the senses of transparency and gradation. With the features of waveform adjustment knobs and trigger level adjustment knob, GW Instek provides a very thoughtful design -the zero key function, which allows engineers to work more effectively. For mathematical analysis mode, 1Mpts FFT signal display makes the dull frequency domain signal analysis more delicate. Options such as the serial bus decoding function, the waveform search function, and the segmented memory function also arm the GDS-1000B Series with more advanced measurement technologies. Moreover, the innovative exterior design and compact size also conveniences to users. Other diversified and charming multi-functional operation demonstrates the concept of complete technology integration.

A. WAVEFORM UPDATE RATE UP TO 50,000wfms/s

The GDS-1000B Series oscilloscope is under the category of general and fundamental oscilloscope by the market segmentation. Nevertheless, the series aims itself with the waveform update rate up to 50,000wfms/s. Users can input a rapidly frequency modulation carrier signal as shown on the diagram. An unsmooth temporarily holding phenomenon will occur while using conventional digital oscilloscopes to measure this signal. As a result, the conventional digital oscilloscopes could not clearly yield the modulation variation process of frequency modulation signals. With the GDS-1000B Series oscilloscope, the measurement result will produce not only a smooth waveform modulation variation, but also distinguish the different layers. Engineers could easily grasp the root cause of electric circuits while measuring the unexpected and fast changing signals. The GDS-1000B Series is indeed an excellent debugging weapon for the test and measurement industry.

B. 256 COLOR GRADIENT DISPLAY

With respect to the waveform display technology, the GDS-1000B Series oscilloscope is capable of displaying 256 color gradients which can delineate the profound gradational fluctuations; as if it can recreate the analog oscilloscope display experience. Due to the multi-layer video signal is input, the GDS-1000B Series, with 256 color gradient display, has the ability to precisely reveal the colored burst signal and to show details of layers with the brightness. Hence, the dull monochrome waveform is imbued with vitality, which is precisely the unlimited measurement illustration the GDS-1000B Series intents to bring to the general purpose oscilloscope arena.

C. 10M MEMORY DEPTH PER CHANNEL INDEPENDENTLY

The GDS-1000B Series oscilloscope has a powerful and incomparable memory depth for the data retrieving. 10M memory depth per channel independently surpasses the specification of the industry's 1000 Series brushing. 10M memory depth allows users to easily seize the waveform detail while conducting fundamental measurement operations. Users can input a signal with a long period in trace and the time scale is adjusted to 1ms/div, then GDS-1000 Series oscilloscopes for lack of sufficient memory depth will appear a distorted waveform while sampling the waveform for its details. The GDS-1000B Series while enlarging the waveform to 20ns/div reveals a very clear sine waveform detail which is precisely the true value of the GDS-1000B Series oscilloscope.

D. 1M FFT MATHEMATICAL SAMPLING ANALYSIS MODE

The GDS-1000B Series oscilloscope, under the Fast Fourier Transform mathematical analysis mode, is equipped with the 1M memory depth retrieving mode. For the conventional digital oscilloscopes, the FFT mode is only with 2k memory depth. Therefore, it is difficult to take into the strength distribution of each spectrum quantity under the frequency domain mode. The GDS-1000B Series oscilloscope leads the industry to provide the display mode of 1M retrieving points, which can observe the detail of each spectrum quantity. On top of that, the 50,000 wfms/s waveform update rate and the 1GSa/s real time sampling rate are as precise as if a real time spectrum analyzer is used. These features substantially elevate oscilloscope's signal processing capability for the frequency domain analysis. The diagram shows a 200 Hz carrier waveform to be modulated as a standard FM signal with 40 kHz carrier frequency and 1 kHz modulation frequency. The GDS-1000B Series is equipped with 1M memory depth, a 14 bits frequency domain resolution can be clearly revealed that allows engineers to fully grasp the measurement details.

E. ZOOM IN/PLAY AND PAUSE FUNCTION

The GDS-1000B Series oscilloscope provides engineers with partial waveform zoom in function to observe waveform in great details. The display screen can be split into two windows: the upper window shows waveform data log in a long period of time and the marked vicinity of the waveform needed to be zoomed in will be displayed in the enlarged partial waveform. The function not only allows engineers to make a comparison but also grasp waveform details in the different timeframe. Additionally, the GDS-1000B Series also features the play/pause function for the engineers working for the observation. the play/pause function facilities engineers to rapidly shun through the whole section of DUT's waveforms as well as to swiftly identify waveform's problems.

F. DIVERSIFIED TRIGGER FUNCTIONS

The GDS-1000B series oscilloscope is equipped with diversified trigger functions, including Edge Trigger, Delay Trigger, Pulse Width Trigger, and Video Trigger. Engineers, based upon different waveform measurements, can choose different trigger functions to set it shown waveforms in order to identify the root cause of the complicated circuit designs to save development time and to accomplish tasks.

G. X-Y MODE DISPLAY



The GDS-1000B series oscilloscope provides the educational market with some powerful measurement functions. Among them, the X-Y mode display is one of the examples. Teachers and students can use X-Y mode display to conduct Lissajous diagram teaching, which allows users to easily understand the relation between waveforms and frequency while measuring sine waveforms with different frequency by dual channels. For engineers working for the industries, the X-Y mode display can be used to conduct yield rate tests for basic components' electric conduction and resistance variation. Therefore, the X-Y mode display plays an important role in basic oscilloscopes.

H. GO/NOGO FUNCTION

For the industries, the yield rate determination is very important to mass production. The GDS-1000B series oscilloscope provides the Go/NoGo analysis function to accelerate the yield rate analysis. From the right diagram, the Go/NoGo function provides a standard waveform template for examining DUT's waveforms. The function can freely adjust the zone of template. A defect message will be shown if the DUT's waveform is abnormal and touches the template. The function is not only very useful measurement tool for production lines but also a very convenient tool for engineers to observe waveforms in a long period of time.

I. DIGITAL VOLTAGE METER FUNCTION

For electric circuit measurement and debugging, R&D engineers require oscilloscopes as well as basic voltage meters. The GDS-1000B series oscilloscope equips with a digital voltage meter with three-digit voltage value and an eight-frequency value. Engineers, by pressing the option key, can select the digital voltage meter function from the menu to measure DC,AC voltage, duty cycle, and frequency. Engineers can not only measure waveforms but also monitor the numerical variations of each waveform on the circuit board. The function is a very convenient tool.

* Users need to download this application from GW Instek website

J. DATA LOG FUNCTION

The GDS-1000B Series oscilloscope has the data log function option, which allows users to observe and record waveform changes in a long period of time to ensure product's reliability and stability. The data log function can set data storage time and interval based on the test requirements. For example, if the storage time is set as 1 hour and the interval can be set as 5 seconds the shortest. Data log formats include waveform and point data in CSV file. Data can be saved to USB, GDS-1000B or remote computer via LAN. It is very user-friendly and also an advanced measurement management tool.

* Users need to download this application from GW Instek website

K. DIGITAL FILTER FUNCTION

In electric circuit tests, engineers are often troubled by noise interference while measuring signals. The GDS-1000B series oscilloscope provides the digital filter function option, which can be set as high pass or low pass filter. The filter frequency can be adjusted according to the requirements. The filter parameters of each channel can also be set. The tracking function can be used to set scores filter frequency for all channels.

* Users need to download this application for CW Instek website

L. 36 MEASUREMENT PARAMETER SELECTIONS

The GDS-1000B series oscilloscope is equipped with 36 different automatic measurement parameter functions. Users, after obtaining measured waveforms, can select different measurement parameters from Measure key according to different measurement requirements. The GDS-1000B Series shows simultaneously the latest sets of different measurement parameters on the bottom of the display screen. Users can also select to show all parameters if the preset eight sets are insufficient. Once the selection is made, all 36 measurement parameters will be shown on the center of the display screen. This is a very convenient measurement tool for students writing dissertations or engineers writing reports.

PANEL INTRODUCTION

1. 7 inch WVGA LCD Display
2. 1GSa/s Real-Time Sampling Rate
3. Zoom and Play/Pause
4. Math Computing, Waveform Reference
5. Demonstration Output and USB Port
6. Connecting Interface : USB, LAN
7. Ctrl, and Go/NoGo Output

M. OPEN/AVE CONNECTION SOFTWARE

The GDS-1000B Series oscilloscope, via the OpenWave connection software developed by GW Instek, can connect with the PC. Users, after installing USB driver under Windows interface, can connect GDS-1000B with the PC through USB cable and OpenWave software. Waveform interpretation and retrieval can be done from the PC end. Data retrieval and storage can further facilitate users in processing analysis. OpenWave connection software is indeed a very powerful tool for engineers to compile reports or to integrate systems.

4 Channel Model

GDS-1104B 100MHz
GDS-1074B 70MHz
GDS-1054B 50MHz

2 Channel Model

GDS-1102B 100MHz
GDS-1072B 70MHz

SPECIFICATIONS

		GDS-1054B	GDS-1074B	GDS-1074B	GDS-1102B	GDS-1104B
VERTICAL	Channels	4	4	4	2	4
	Bandwidth	DC-50MHz(-3dB)	DC-70MHz(-3dB)	DC-70MHz(-3dB)	DC-100MHz(-3dB)	DC-100MHz(-3dB)
	Rise Time	7ns	5ns	5ns	3.5ns	3.5ns
	Bandwidth Limit	20MHz	20MHz	20MHz	20MHz	20MHz
	Vertical Sensitivity Resolution	8 bit 1mV/div~10V/div				
	Input Coupling	AC, DC, GND				
	Input Impedance	1MΩ±2.1%pF approx.				
	Probe Attenuation Factor	1X, 10X, 100X, 1000X				
	Polarity	Normal/Inverted				
	Maximum Input Voltage	300Vrms, CAT I; 600Vrms CAT II with GTP-070B- A/300V A 10:1 probe				
	Waveform Offset Range	1mV/div~200mV/div: ±8.0V ; 200mV/div~1V/div: ±12V ; 1V/div~10V/div: ±120V				
	Waveform Signal Process	+, -, ×, ÷, FFT, FFTrms, User Defined Operation (+FFT, FFTrms, FFT Spectral magnitude, Set FFT Vertical Scale to Linear RMS or dB VRMS, FFT Window Display : Rectangular, Hamming, Hanning, or Blackman-Harris				
TRIGGER	Source	CH1, CH2, CH3, CH4, Line, External, External/5 (Available models only)				
	Trigger Mode	Auto (supports Roll Mode at 50 ms/div and slower), Normal, Single Sequence				
	Trigger Type	Edge, Pulse Width, Video, Pulse Run, Rise & Fall, Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay (4ns~10s), Setup, Hold (4ns, 8ns)				
	Holdoff range	4ns to 10s				
	Coupling	DC, DC LF rej., HF rej., Noise rej.				
	Slope	Rising, Falling				
EXTERNAL TRIGGER	Range					
	Sensitivity	DC ~ 100MHz: Approx. 100mV ; 100MHz ~ 200MHz: Approx. 150mV				
	Maximum Input	300Vrms				
HORIZONTAL	Time/Div Range	5ns/div ~ 100s/div (1-2-5 increments)				
	ROLL	100ms/div ~ 100s/div				
	Time/Div Range	5ns/div ~ 50ns/div				
	Field Digitizer	20,000 (50 div maximum)				
	Timebase Accuracy	±50 ppm over any 41 ms time interval				
	Record Length	10M/ch				
	Record Length	Max. 50Kpts				
	Acquisition Mode	Normal, Average, Peak Detect, Single				
	Interpolation	Sin(x)/x, Linear				
	Average	2, 4, 8, 16, 32, 64, 128, 256				
X-Y MODE	X-Axis Input	Channel 3, Channel 3*(1%) (Dual-channel models only)				
	Y-Axis Input	Channel 4, Channel 4*(1%) (Dual-channel models only)				
	Phase Shift	±3° at 100kHz				
CURSORS AND MEASUREMENT	Cursors	Amplitude, Time, Gating available; Unit : Seconds(s), Hz(1/s), Phase(degree), Ratio(%)				
	Automatic Measurement	36 of the following: Mean, Min, Amplitude, High, Low, Mean, Cycle Mean, Cycle RMS, Area, Cycle Area, RMS/Vrms, Cycle RMS/Vrms, Std Dev, Pk-Pk, Min, Max